



User Manual

LLG-Digital Pocket Thermometer type 12090

Art.-No: 9.236 707

Functions:

- on/off
- H/T
- °C/°F
- One hour auto shut of

Feature:

- 85 x 3,5 mm stainless steel sensor probe
- 1 second normal temperature sensing time
- Piercing probe
- Plastic sleeve

Specification:

- Measurement range: -50 °C ~ + 150 °C or -58 °F ~ +302 °F
- Resolution: $\pm 0,1^\circ$ for -19,9° ~ + 199,9°, otherwise 1°
- Accuracy: $\pm 1^\circ\text{C}$ in the range of -30 °C ~ +150 °C, otherwise more than $\pm 2^\circ\text{C}$
 $\pm 1,8^\circ\text{F}$ in the range of -22 °F ~ +302 °F, otherwise more than $\pm 4^\circ\text{F}$
- Ambient temperature for plastic casing: 0 °C ~ +50 °C or +32 °F ~ + 122 °F
- Battery: 1x 1,5 V LR 44

Installation:

- Unpack the thermometer with care.
- Open the battery doors, install the battery into the battery compartment. Then close the battery door.
- Sliding plastic sleeve. The thermometer is now ready for use.
- Replace new battery when the low battery indicator appears on the display.
- Attention: Please dispose this thermometer properly! Not in the domestic waste!

Operation:

- Slide/Press the "**ON/OFF**" switch/button. All functions will show on the display. The thermometer is ready for use.
- "**°C/°F**": select desired temperature unit
- "**H/T**": press once "**HOLD**" flash to retain reading for recording

Precautions:

- To obtain the best results, the probe tip should be immersed at least 10 mm into the tested substance.
- Make sure the batteries are installed with the correct polarity as shown in the battery compartment.
- Remove the battery from the battery compartment if the thermometer will not be used for long duration of time or during storage.
- The thermometer cannot be used or put inside any oven or microwave.
- Place the plastic O-Ring at the appropriate position after opening the battery door to ensure the water-proof function.

Changing battery:

